



REALFICTION™

HOW TO MAKE MOVIES PLAY AND LOOP AUTOMATICALLY ON DREAMOC XL4

- FAIL_OVER

When adding content to your USB you need to add a FAIL_OVER folder and place your content inside the folder.

CREATING A FOLDER ON YOUR USB WITH FAIL_OVER

This feature automatically playback the video files in the FAIL_OVER folder, if the screen is programed to FAIL_OVER mode. All XL4 products from REALFICTION is programed to use FAIL_OVER mode from the factory.

Create a folder on your USB stick

- Put your USB stick in your computer
- Add a folder to the USB stick called FAIL_OVER (it is important it is written in capital letters and with hyphen between.
- Add your content inside the folder
- Eject the USB and place in the Dreamoc XL4

If your Dreamoc XL4 is not programed to FAIL_OVER, this can be done the following way

- Click the EXIT button on the remote control
 - No signal menu will now appear on the screen
- Click the Settings button on the remote control (the tooth wheel)
- Choose EZ Settings
- Move the curser to "Fail Over" icon and click OK
- In the Fail Over menu make the following settings:
 - Mode = Auto
 - USB = Movie
- Choose back. The content in the FAIL_OVER folder will now be played.